

# Quick Start Guide

## Getting Started

Thank you for purchasing the VIPER home monitoring and security system starter kit. The VIPER home starter kit includes everything you need to monitor one entry point and detect motion in one room. The system also has home control expandability. Visit [www.viper.com](http://www.viper.com) for additional product and warranty information.

## What's Included




## What's Needed

- Computer with internet connection
- Internet access point with RJ-45 port (required for the Central Controller connection)
- Tape measure (used when mounting the motion sensor)
- A coin to open the door / window sensors for battery installation

**Note:** The 8 digit serial number is located on the bottom of the Central Controller and inside the battery compartment.

Record serial number here: \_\_\_\_\_




## Connecting the Central Controller

**Step 1** Install the backup battery first by removing the Central Controller battery cover to and then reattach once installed.



**Step 2** Connect the ethernet/LAN cable to the Central Controller and your wireless router/modem.



**Step 3** Plug the power adapter into the back of the controller and the other end into the home wall outlet.




**Step 4** The LED is amber upon turn on and changes to green once the connection process is complete.



## Registration of System and Services


**Step 1** After confirming that the Central Controller displays a green light. Please visit [home.viper.com](http://home.viper.com) to begin the registration process.

Select Go to first time registration page



Click Register


**Step 2** Enter your 8 digit Central Controller serial number recorded at that top of this page and click next. If you receive an error, please confirm the panel LED is green.



**Step 3** Complete the registration process as shown below. Keep note of your e-mail, password, and user code. These are used to log into the smartphone app.




**Step 4** Registration is complete when the VIPER home managements center opens. You are now ready to install each of the sensors.



Select each of the devices and name them for the location they will be placed.


Installing Sensors

**Step 1** Install batteries in each of the sensors as shown below.




Need installation help? Instructional videos and more can be found online at: [www.viper.com](http://www.viper.com)


**Step 2** Mount the door/window sensors in the desired location. Align the dots across from each other when the door or window is in the closed position, any space between them should be less than 3/4".



**Step 3** Mount the motion sensor in a corner or on a flat wall. Avoid mounting in direct sunlight and make sure it is at least 4" from the ceiling and 72" from the floor.



**Other** Additional accessories available at Best Buy and Online




Connecting the App


**Step 1** Download the ViperConnect app from the App Store for iPhone/iPad, and Google play for Android devices. Scan QR code below to download app.




**Step 2** Once the app has been downloaded, it takes you through a quick tutorial of the features. Once complete, click the login button.



**Step 3** Log into your account with user name (e-mail address), password, and 4 digit user code.



**Step 4** Once logged in successfully, you are directed to the app screen (below) where you can access the entire suite of VIPER connected products. Launch Home Control.



Using the App

**Step 1** Use buttons to Arm (away & stay), Disarm, Panic, and receive current system status.




**Step 2** Access live video\* feed on demand and receive alerts with recorded video of any intruders. \* Indoor camera with motion detector required.




Premium service plan required

**Step 3** Control lights, thermostats, garage doors, locks, and more from your smartphone with ViperConnect and the Z-wave® Bridge (sold separately).



Premium service plan required

**Step 4** View history by all users; arm, disarm, accesses, intrusion alerts, and videos. All history is saved for 60 days.



Premium service plan required